

# Advance Security



## HD Exit Sign Emergency Light Hidden Camera Hard Wired

Full 1080p HD video for an amazing picture. Uses HD-CVI format

Part Number: SSC-866CHD

<http://www.surveillance-spy-cameras.com/hd-exit-sign-emergency-light-hidden-camera.htm>

### Specifications

Wiring Wires Directly Into 110-120VAC to power exit sign emergency light and camera

### Camera Specifications

Sensor	1/2.9 inch SONY CMOS
Lens	Choice of Board or Pinhole
System	NTSC
Effective Pixel	1928(H) × 1088(V)
Illumination	0.001 LUX / F1.2
Resolution	AHD/TVI/CVI: 2.4mp 1080P, Analog: 2000TVL
Resolution Change	Push Button L,R,U or Down for 5 Seconds
Scanning Frequency	50Hz 60Hz
Gamma	0.45
Electronic Shutter	1/60~1/100000s
S/N	>46dB
Video Output	1.0V p-p Shift to TVI/CVI/CVBS by OSD
Operation Temperature	-20 °C to 50 °C
Working Humidity	less than 95%
Power	DC12V (±10%)
Language	Press button, scroll down 4 lines to pair of arrows and press button

### Package Includes

- HD Exit Emergency Light Hidden Camera